

| 1-Gang Specialty Boxes | | | 2-Gang Specialty Boxes | | |
|---|----------------|--|---|-----------------------|--|
| Description | Color | 1-Gang | Description | Color | 2-Gang |
| Low Profile Switch/Receptacle Base has 1/2" trade size KOs. | Ivory White | HBL5748SIVA HBL5748SWA A: 4.54" (115.32) B: 2.82" (71.63) C: 1.13" (28.70) | Alarm Device Box Surface mounting of alarm devices and safety signals. | Ivory White Red | HBL5752IVA — HBL5752RA A: 4.54" (115.32) B: 4.64" (117.86) C: 1.38" (35.05) |
| Combination Switch/Recept. Connects surface runs of 1/2" trade size conduit, one raceway twistout each side and three raceway twistouts top and bottom. | Ivory White | HBL5745IVA HBL5745WA A: 4.54" (115.32) B: 2.82" (71.63) C: 1.75" (44.45) | Extra Deep Alarm Device Box For surface mounting of alarm devices and safety signals. Cover is 2.75" (69.85) deep. | Ivory White Red | HBL5753IVA — HBL5753RA A: 4.54" (115.32) B: 4.64" (117.86) C: 2.75" (69.85) |
| Utility Box* For use as a tee, cross, pull box, junction box or blank box. Base has 1/2" trade size KOs. | Ivory White | HBL57242IVA HBL57242WA A: 4.12" (104.78) B: 2.00" (50.80) C: 1.39" (35.31) | Distribution Box Twistouts permit three parallel raceway runs on each side. Cover takes devices with mounting screw centers of 2.75" (69.85), 3.5" (89.00), 4.0625" (103.00) and canopy fixture not larger than 4.625" (117.00). Can be used with HBL5736IV (blank cover) to create junction box. | Ivory White | HBL5735IVA — A: 4.54" (115.32) B: 4.64" (117.86) C: 1.38" (35.05) |

Note: *Use catalog number HBL5791 for connecting 1/2 in. EMT to HBL5745 and HBL57242 boxes.



| Round Boxes | Description | Color | 4.75 inches O.D. | 5.50 inches O.D. | 6.38 inches O.D. |
|---|---|--|--|--|--|
| | Extension Box (Open Base) For mounting on 3.25" (83.00) or 4" (102.00) round or square conduit boxes or other recessed outlets. Cover takes any device with mounting screw centers of 2.75" (69.85), 3.5" (89.00) and 4.06" (103.00). | Ivory White | HBL5737IVA HBL5737WA A: 1.02" (26.00) B: 4.75" (120.65) | HBL5737AIVA HBL5737AWA A: 1.02" (26.00) B: 5.50" (140.00) | HBL5739AIVA — A: 1.02" (26.00) B: 6.38" (162.01) |
| Fixture Box (Solid Base) To hang fixtures. Cover takes any device with mounting screw centers of 2.75" (69.85), 3.5" (89.00) and 4.06" (103.00). Both boxes can be used as a pull or junction box when used with HBL5736IV/W (blank cover). | Ivory White | HBL5738IVA HBL5738WA A: 1.02" (26.00) B: 4.75" (120.65) | HBL5738AIVA HBL5738AWA A: 1.02" (26.00) B: 5.50" (140.00) | HBL5739IVA HBL5739WA A: 1.02" (26.00) B: 6.38" (162.01) | |

| Specialty Round Boxes | Description | Color | Catalog Number | Round Covers | Description | Color | Catalog Number |
|---|---|--|--|--------------|---|----------------|--|
| | Outlet Box For devices with mounting screw centers of 1.47" (37.00), 1.63" (41.00), 1.69" (44.00) or 1.84" (46.00). | Ivory White | HBL5733IVA — A: 1.02" (26.00) B: 3.00" (76.00) | | Blank Cover For use with HBL5733IVA. Has 1/2" trade size KO in center. | Ivory White | HBL5731IV — A: .24" (6.10) B: 2.40" (60.96) |
| | Fanbox with Solid Base Cover accepts fan bracket with mounting centers of 3.2" (81.00). Rated for fans and fixtures up to 50 lbs. | Ivory White | HBL5738AFIVA HBL5738AFWA A: .38" (9.75) B: 4.19" (106.30) | | Blank Cover For use with HBL5735IVA, HBL5737IVA/WA, HBL5737AIVA/WA, HBL5739AIVA, HBL5738IVA/WA, HBL5738AIVA/WA and HBL5739IVA/WA. Has 1/2" trade size KO in center. | Ivory White | HBL5736IV HBL5736W A: .38" (9.75) B: 4.19" (106.30) |
| Retrofit Box for Fire Alarm Detectors For installing round alarm sensors. | Ivory White | HBL5739AABIVA HBL5739AABWA A: 1.62" (41.15) B: 6.50" (165.10) | | | | | |

Dimensions in Inches (mm)